

PAM150 Series Power Supply

Standard Models
PAM150-X-Y₁...Y_n

Tailored Models
PAM150-60ZZZ

Custom Models
PAM150-61ZZZ

	Voltage and Current Ratings		Standard Options
X Codes	Volts	Amps	"Y" Code Descriptions
1	Not Available		A 12Vdc, 0.5A Auxiliary Output** B Droop Share* C Fan Assembly** E DCOK Invert F PF Invert G Field configurable options – B, I, and J I Single Wire Share* J Square Current Limit K Molex Connector, 7A max. (#8 studs standard) M Metric Mounting O ORing Diode R Remote On/Off (closed is OFF) S Remote On/Off Invert (open is OFF) *Includes Option J **Options A and C are not available together
2	3.3	30.0	
3	5.0	30.0	
4	12.0	12.5	
5	15.0	10.5	
6	24.0	6.5	
7	28.0	5.5	
8	36.0	4.5	
9	48.0	3.5	
			Tailored Units (no safety changes): ----- 60ZZZ, where ZZZ = Factory Assigned Number Harnesses Added, Special test data, Etc.
			Custom Units (safety critical changes) ----- 61ZZZ, where ZZZ = Factory Assigned Number